


BANDPASS FILTER

085 VHF cavity

Double cavity bandpass filter the VHF range can be allocated in one half 2 unit 19" cabinet. Frequency tuning is manually regulated through mechanical knobs.



FPB085-V/2

Electrical Specifications

Frequency band:	112 - 156 MHz
Impedance:	50 Ω
Max Power	50W CW
Insertion loss:	2 dB

Mechanical Specifications

Connector Type:	N Female
Dimensions:	½ 19" rack, 2HU, depth 560 mm
Operating temp.:	-10°C to +55°C
Tuning method:	Rotary knobs, telescopic movement

Bandpass Filters	Channels	Cabinet 2HU	Attenuation
FPB085-V/2	1	½	20dB ± 0.4% from f_0 35 dB ± 1% from f_0